



© Copyright
International Business
Machines Corporation 1995.
All Rights Reserved.

References in this
publication to IBM
products or services do not
imply that IBM intends
to make them available
outside the United States.



30H2388

Printed in U.S.A.


30H2388



S30H-2388-00



Hardware Maintenance Service and Reference



ThinkPad Power Series 820

First Edition (July 1995)

The following paragraph does not apply to the United Kingdom or any country where such provisions are inconsistent with local law: INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer or express or implied warranties in certain transactions; therefore, this statement may not apply to you.

This publication could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements or changes in the products or the programs described in this publication at any time.

It is possible that this publication may contain reference to, or information about, IBM products (machines and programs), programming, or services that are not announced in your country. Such references or information must not be construed to mean that IBM intends to announce such IBM products, programming, or services in your country.

Requests for technical information about IBM products should be made to your IBM Authorized Dealer or your IBM Marketing Representative.

IBM may have patents or pending patent applications covering subject matter in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to the IBM Director of Licensing, IBM Corporation, 500 Columbus Avenue, Thornwood, NY 10594, U.S.A.

© Copyright International Business Machines Corporation 1995. All rights reserved.

Note to U.S. Government Users — Documentation related to restricted rights — Use, duplication or disclosure is subject to restrictions set forth in GSA ADP Schedule Contract with IBM Corp.

Safety Information

The following inspection guide will assist you in identifying potentially unsafe conditions on IBM products. Each product, as it was designed and built, had required safety items installed to protect users and service personnel from injury. This guide addresses only those items. However, good judgment should be used to identify potential safety hazards due to attachment of non-IBM features or options not covered by this inspection guide.

If unsafe conditions are present, determine how serious the hazard is, and whether you can continue without first correcting the problem.

Consider these conditions and the safety hazards they present:

- Electrical hazards, especially primary power: primary voltage on the frame can cause serious or fatal electrical shock.
- Explosive hazards, such as a capacitor, can cause serious injury.
- Mechanical hazards, such as loose or missing hardware, can cause serious injury.

The guide consists of a series of steps presented in a checklist. Begin the checks with the power off and the power cord removed from the electrical outlet.

Checklist:

1. Power off the computer. Disconnect the power cord from the electrical outlet.
2. Check exterior covers for damage (loose, broken, or sharp edges).
3. Check the power cord:
 - a. There should be a third-wire ground connector, and it should be in good condition. Use a meter to measure third-wire ground continuity for 0.1 ohm or less between the external ground pin and frame ground.
 - b. The cord should be the appropriate molded type as specified in the parts section of this manual.
 - c. The insulation must not be frayed or worn.
4. Remove the cover.
5. Check for any obvious non-IBM alterations. Use good judgment as to the safety of any non-IBM alterations.
6. Check inside the unit for any obvious unsafe conditions, such as metal filings, contamination, water or other liquids, or signs of fire or smoke damage.
7. Check for worn, frayed, or pinched cables.
8. Check that the power card shield has not been removed or tampered with.
9. Check that all safety labels and information labels are attached correctly.

Contents

ThinkPad Power Series 820 Hardware Maintenance

Service	1
How to Disable the Power-On Password	2
Supervisor Password	3
Power Shutdown Switch	3
General Checkout	4
Undetermined Problems	10
Installed Devices Check	10
Printer	11
Power Systems Checkout	12
AC Adapter Test	14
Battery Pack Test	15
System Power Problems	17
Standby Battery Test	18
Backup Battery Test	19
Travel Quick Charger Test	20
Maintenance Utility	21
System Information	22
SCSI Format	23
Numeric Error Codes	24
Symptom-to-FRU Index	26
No-Beep Symptoms	26
Miscellaneous Symptoms	27
Parts Listing	30
FRU List	31
Option List	33
Accessories	34

ThinkPad Power Series 820 Hardware

Maintenance Reference	37
Product Overview	37
Product Description	38
Options	39
Option Compatibility	39
Accessories	39
Component Descriptions	39
System Board	39
Microprocessor	39
Flash ROM	39
RT/CMOS/NVRAM	39
EEPROM	40
Power Management System	40
LCD	40
Diskette-Drive Controller	40

Serial Port	41
Parallel Port	41
External Input-Device Connector	41
External Display Connector	41
Operating Requirements	42
Power-On Self-Test (POST)	42
Memory Requirements and Limitations	42
Specifications	43
System	43
AC Adapter	44
Travel Quick Charger	44
Special Tools	45
Repair Information	46
Removals and Replacements	47
1000 Opening the Display Assembly	47
1005 Opening the Keyboard Assembly	48
1010 Speaker Assembly	49
1015 Battery Pack	50
1020 HDD Assembly	51
1025 FDD Assembly	52
1030 CD-ROM Drive Assembly	53
1035 DIMM (Memory) Card	54
1040 Backup, Standby Battery	55
1045 Center Cover Assembly, Mic Assembly	56
1050 Keyboard Assembly	57
1055 Display Assembly	58
LCD FRU Replacement Notice	58
1060 Shield Assembly	61
1065 Interposer Card, DC/DC Card	62
1070 CPU Card	63
1075 Video Card, System Board	64
1080 Audio Card	66
1085 Memory Board	67
Locations	68
Front View	68
Bottom and Rear Side View	70
Inside View	71
System Board Connectors	72

Read This First

Before you go to the checkout guide, be sure to read this section.

Important Notes

- **Only certified trained personnel should service the computer.**
- **Be extremely careful during write operations such as copying, saving, or formatting.** Drives in the computer that you are servicing might have been rearranged or the drive startup sequence might have been altered. If you select an incorrect drive, data or programs can be written over.
- **Replace FRUs only for the correct model.** When you replace the FRU, make sure the model of the machine and FRU part number are correct by referring to the part list.
- **FRUs should not be replaced because of a single, unreproducible failure.** Single failures can occur from a variety of reasons that have nothing to do with a hardware defect—for example, cosmic radiation, electrostatic discharge, or software errors. FRU replacement should only be considered when a recurring problem exists. If this is suspected, clear the error log and run the test again. Do not replace any FRUs if log errors do not reappear.
- **Be careful not to replace a nondefective FRU.**
- Do not forget to return the original FRU if you find the suspected or replaced FRU is not the cause of the original problem or symptom.

How to Use Error Messages

Use the error codes displayed on the screen to diagnose failures. If more than one error code is displayed, begin the diagnosis with the first error code. The cause of the first error code can result in false error codes being displayed. If no error code is displayed, see if the error symptom is listed in the "Symptom-to-FRU Index" on page 26.

How to Diagnose Multiple FRUs

When the adapter or device has more than one FRU, the error code could be caused by a single FRU. Before replacing several FRUs, try removing or exchanging each FRU, one by one in the designated sequence, to see if the symptoms change.

What to Do First

The servicer must include the following in the parts exchange form or part return form that is attached to the returned FRU.

- ___ 1. Name and phone number of servicer.
- ___ 2. Date of service.
- ___ 3. Date when part failed.
- ___ 4. Date of purchase.
- ___ 5. Failure symptoms, error codes appearing on display, and beep symptoms.
- ___ 6. Procedure index and page number in which failing FRU was detected.
- ___ 7. Failing FRU name and part number.
- ___ 8. Machine type, model number, and serial number.
- ___ 9. Customer's name and address.

Before checking problems with the computer, determine whether or not the damage applies the warranty by referring to the following:

Note for Warranty: During the warranty period, the customer may be responsible for repair costs if the computer damage was caused by misuse, accident, modification, unsuitable physical or operating environment, or improper maintenance by the customer. The following list provides some common items that are not covered under warranty and some symptoms that may indicate the system was subjected to stresses beyond normal use:

The following is not covered under warranty:

- A cracked LCD panel caused by the application of excessive force or from being dropped.
- Scratched (cosmetic) parts.
- Cracked or broken plastic parts, broken latches, broken pins or connectors if the damage was caused by excessive force.
- Damage caused by liquid spilled into the system.
- Damage caused by the improper insertion of a PCMCIA card or the installation of an incompatible card.
- Damage due to foreign material in the FDD.
- Diskette drive damage caused by pressing the diskette drive cover or inserting diskettes with multiple labels.
- A bent or damaged diskette eject button.
- CD-ROM drive damage caused by the application of excessive force from being dropped.
- A fuse blown from the attachment of a nonsupported device.
- Inability to use the computer because the password was forgotten.

If the following symptoms are present, they may indicate damage caused by nonwarranted activity:

- Missing parts may be a symptom of unauthorized service or modification.
- HDD spindles can become noisy if subjected to excessive force or if they are dropped.

FRU Service Notice

Review these service notice *before* replacing a FRU.

LCD FRU Replacement Notice

If missing or discolored dots appear on the LCD, carefully read the following note to determine whether you should replace the LCD or not.

Important

A small number of missing, discolored, or lighted dots (on all the time) is characteristic of LCD technology, but excessive pixel problems can cause viewing concerns. The LCD should be replaced if the number of dots satisfies either of the following conditions:

- The number of missing, discolored, or colored dots in any colored background is 21 or more.

ThinkPad Power Series 820 Hardware Maintenance Service

Important

If you are not familiar with the IBM* ThinkPad* Power Series* 820 safety information, begin by reading "Safety Information" on page iv. Then continue with the service or reference sections of this manual as required.


The service section of this manual provides the necessary information for a trained service representative to diagnose a failure to the field-replaceable unit (FRU).

This section includes:

- Password overriding
- General checkout
- Undetermined problems
- Power systems checkout
- Various computer tests
- Symptom-to-FRU index
- FRU codes
- Parts listing

* Trademark of the IBM Corporation.

How to Disable the Power-On Password



Do the following to disable the power-on password:

1. Power off the computer.
2. Open the display assembly and keyboard assembly. (See “1000 Opening the Display Assembly” on page 47 and “1005 Opening the Keyboard Assembly” on page 48.)
3. Remove the battery pack. (See “1015 Battery Pack” on page 50.)
4. Remove the CD-ROM drive or diskette drive. (See “1030 CD-ROM Drive Assembly” on page 53 or “1025 FDD Assembly” on page 52.)
5. Identify and install a jumper on the J17 connector on the system board.
6. Power on the computer.

Note: Remove the jumper from the J17 connector after you have finished the service action.

To enable the password again, select **password** on the **Easy-Setup** screen; then enter the password.

Supervisor Password

The supervisor password is a security feature that is used to protect the system from unauthorized use. No overriding is provided. Obtaining permission from the password owner to unlock the password is a prerequisite for running diagnostic tests and performing service.

Power Shutdown Switch

The power shutdown switch is located on the rear side of the system unit. This switch forces the computer power off when the power switch does not work because of a system hang.

General Checkout

The diagnostic tests are intended to test *only* IBM products. Non-IBM products or modified options can give false errors and invalid responses.



Important

If more than one error code appears, diagnose the first error code first. The cause of the first error code can cause additional false error codes to appear. Multiple error codes may appear on the LCD during the POST process.

001

- Power off the computer and all external devices.
- Check that all cables and the power cord are correctly connected.
- Make sure there are no diskettes in the diskette drive.
- Set all display controls to their middle positions.
- Power on all external devices.
- Power on the computer while holding down the **F1** key. Check for the following responses:
 - The power-on indicator lights.
 - One short beep sounds.
 - The **Easy-Setup** screen or **Power-On Password** screen appears.

DID EITHER THE EASY-SETUP OR POWER-ON PASSWORD SCREEN APPEAR?



Yes No

002


Press the **Ctrl + E** keys to display the **Error Log** screen. Go to Step 004.

003

- If the **Power-On Password** screen appears, enter the password or disable the power on password. (See "How to Disable the Power-On Password" on page 2.)
- Select **Test** on the **Easy-Setup** screen; then go to Step 007 on page 6.

004

WERE ANY ERRORS LOGGED?



Yes No

005

(Step 005 continues)

(continued)

005 (continued)


- Press the **Enter** key to exit the error log and select **Test** on the **Easy-Setup** screen; then go to Step 007.

006

- Note all error codes on the screen; then clear the error log. Go to “Numeric Error Codes” on page 24 and find the error code; then follow the instructions. If the problem remains, go to “Undetermined Problems” on page 10.

007

DID THE TEST MENU APPEAR?



Yes No

008

- Go to “Symptom-to-FRU Index” on page 26 and find the error code or the symptom and follow the instructions. If the problem remains, go to “Undetermined Problems” on page 10.

009



Press the **Ctrl + A** keys and select **Super Test** on the **Test** screen; then go to Step 010.

010

(Step 010 continues)

010 (continued)

DID EITHER THE SUPER TEST OR SUPER PASSWORD SCREEN APPEAR?



Yes No

011

- Go to “Symptom-to-FRU Index” on page 26 and find the error code or the symptom and follow the instructions. If the problem remains, go to “Undetermined Problems” on page 10.

012

- Unlock the supervisor password. (See “Supervisor Password” on page 3.)

(Step 012 continues)

(continued)

012 (continued)

IS THE DISPLAYED ICON CORRECT WITH THE INSTALLED DEVICES ON THE SUPER TEST SCREEN?

Note: The icons of the installed devices are displayed.

Yes No


013

– Go to “Installed Devices Check” on page 10.

014

Select **Select All** or the specific icon you want to test; then select **Test**. Go to Step 015. (Diagnostic tests will run on all devices in which icons are displayed.)

The serial, parallel, and PC cards icons have the wrap test option. When you run the wrap test, install the wrap plug on each connector and click the icon twice; then select **Test**.



The FDD icon has a scratch diskette test option. When you run the scratch diskette test, install the scratch diskette into the FDD and click on the icon twice; then select **Test**.

The CD-ROM drive icon has a CD-ROM test option. When you run the CD-ROM test, install a CD-ROM into the drive and click on the icon twice; then select **Test**.

015

(Step 015 continues)

015 (continued)

DID THE TESTS DETECT A FAILURE?

Note: If the test stops or hangs when the test is running, replace the last device that was tested.

Yes No

016

The error was not detected by the test:

- Check that the cables and connectors are not damaged.
- Reconnect all adapters, drives, and modules; then test the system several times. A **Loop Test** option is available for looping the tests. To exit the loop test, press the **Ctrl + C** keys between each test.
- If no error is detected, go to “Symptom-to-FRU Index” on page 26. Find the symptom and follow the instructions.
- If any errors are detected, go to “Numeric Error Codes” on page 24.

017

– Note the error codes shown on the screen. Go to “Numeric Error Codes” on page 24 and replace the appropriate FRU.

Undetermined Problems

1. Power off the computer.
2. Remove or disconnect any external device or cables.
3. Power on the computer and run the diagnostic tests.
4. If the symptom remains, repeat steps 1, 2, and 3 until you find the failing adapter or device.
5. If all devices are disconnected and the symptom remains, go to "Power Systems Checkout" on page 12. If this does not resolve the problem, replace the system board.
6. If an intermittent problem remains after replacement of the FRUs, consider external electrical noises that can have an effect on the computer.

Installed Devices Check

If a device is installed but the icon does not appear on the **Test** or **Super Test** screen, the device is defective. Make sure that the device is connected correctly. If the symptom remains, replace the device or the system board.

Parallel and **Serial** icons are always displayed on the **Test** or **Super Test** screen. That is, these icons represent adapters on the system board, not the external devices.

Printer

1. Make sure the printer is correctly connected and power is on.
2. Run the printer self-test, if available. If the printer self-test does not run correctly, the problem is in the printer. Refer to the printer service manual.
3. Disconnect the printer cable.
4. Select **Parallel** on the **Super Test** screen and run the parallel test, if the printer is attached to the parallel port. If the test detects an error, replace the system board. If the test runs error free, replace the printer cable; then run the program to see if the error is re-created. If the problem remains, replace the system board.

Power Systems Checkout

Use the following procedure when you suspect a computer power problem, for example:

- The computer does not power on.
- The computer attempts to power on; then it shuts down immediately.

Obtain from the user all information about the symptoms of the power failure. Before analyzing the power systems, disconnect both the battery pack and the AC Adapter from the computer; then reconnect them to the computer (see note on page 17).

001

DOES THE COMPUTER FAIL *ONLY* WHEN USING THE AC ADAPTER?

Yes No

002

Go to Step 004.

003

– Go to “AC Adapter Test” on page 14 and do the test.

004

DOES THE COMPUTER FAIL *ONLY* WHEN USING THE BATTERY PACK?

Yes No

005

– If the problem occurs *both* in AC Adapter operation and in battery pack operation, go to “System Power Problems” on page 17.

006

DOES THE BATTERY PACK POWER BECOME LOW QUICKLY?

Yes No

007

(Step 007 continues)

007 (continued)

Go to “Battery Pack Test” on page 15.

008

– Using the AC Adapter, do the **Super Test** from the **Easy-Setup** screen. Select **Select All** to test all devices. Go to Step 009.

009

DID THE TESTS RUN SUCCESSFULLY?

Yes No

010

If any error code is displayed, go to “Numeric Error Codes” on page 24.

If nothing is displayed, go to “Symptom-to-FRU Index” on page 26 and replace the appropriate FRU.


011

– Go to “System Power Problems” on page 17 and do the open/short circuit test.

AC Adapter Test

Do the following to analyze an AC Adapter problem.

1. Unplug the AC Adapter from the power outlet and the computer.
2. Inspect the AC Adapter for any signs of overheating or damage.
3. Inspect the AC Adapter power cord for cuts or damage. Replace the power cord, if necessary.
4. Plug the power cord into the power outlet. Listen for any sound that might indicate defective operation.
5. Measure the output voltage at the AC Adapter plug between pins 1 and 3.



Pin	Voltage (V dc)	Signal Name
1	+17.8 to +21	dc output
2		VCCSEL# (VCCC mode select signal)
3	dc ground	RTN
4		Open


- If the voltage is incorrect, but not 0, replace the AC Adapter.
- If the voltage is 0, check the power cord and the power outlet.
- If the power cord and power outlet are OK, replace the AC Adapter.
- If the voltage is correct, suspect a short circuit or a failure in the computer. Go to "System Power Problems" on page 17.

- If the system does not start up when the system is powered on with the battery pack removed and the AC Adapter connected, and if you hear noise coming from the AC Adapter, suspect a short circuit in the computer. Go to the "System Power Problems" on page 17.
- If the system starts up with the battery pack installed and the AC Adapter disconnected, replace the DC/DC card and make sure that the system starts up with the AC Adapter connected. If the system starts up, the original DC/DC card was bad. If the system still does not start up, replace the AC Adapter and reinstall the original DC/DC card. Make sure the system starts up with the new AC Adapter and the original DC/DC card.

Battery Pack Test

Note: When the battery power becomes low, the computer alerts you by sounding three short beeps. When it becomes critically low, the computer generates six long beeps.

1. Remove the battery pack from the computer.
2. Make sure that the storage switch **1** on the battery pack is in the ON (I) position.
3. Measure the voltage between battery pack terminals + and -.



Terminals	Description
+	+8.4 ± 2.1 V dc
S	Data
T	Thermal
-	Ground

System Power Problems

- Charge the battery pack with the power-off charge procedure.
- If the voltage is not correct after the battery pack is charged, replace it.
- If the voltage is correct, suspect a short circuit or failure in the computer. Go to the "System Power Problems" on page 17.
- If the system starts up with the AC Adapter connected, the battery pack removed, and the voltage of the battery pack correct, replace the DC/DC card and check if the system starts up with only the battery pack installed. If the system starts up, the original DC/DC card is failing; if the system still does not start up with the good DC/DC and with the original battery, replace the battery pack and confirm the system starts up with the new battery and with the original DC/DC card.

Do the following to check to see if the thermal protection has tripped:

1. Measure the resistance between terminal (-) and (T).
2. The resistance should be from 2 k Ω to 50 k Ω . If the measured resistance is not in this range, replace the battery pack. If the resistance is between 2 k Ω to 5 k Ω , the temperature of the battery pack is too high for the battery pack to be charged. Do not charge the battery pack until its resistance is more than 5.5 k Ω .

Do the following to analyze a short or an open circuit in the computer:

1. Disconnect *both* the battery pack and the AC Adapter; then reconnect them (see note).
2. Disconnect and then reconnect all external devices from the computer one by one and see if the same symptom appears. If you find a problem with an external device or its associated cables, follow the maintenance procedure for that device.
3. If the same symptom remains with no external devices connected, the problem is in the computer. Visually check the cables, wires, connectors, and cards for short circuits, open wires, or loose or damaged wires. Also check to see if there are any foreign metal material in the computer. Isolate the failing part in the computer by changing the FRUs one by one until you find the problem. Replace the DC/DC card and the system board first.


If the battery power becomes low quickly, and all tests run with no errors detected, replace the battery pack.

4. If the problem remains after you have done all of the preceding, isolate the failure in the computer by changing the FRUs one by one. The most probable failing FRUs are the DC/DC card and the system board.
5. If the battery power becomes low immediately after power-on and no problems are found in other parts of the computer and all internal tests run without detecting any errors, replace the battery pack.

Note: If the power protection mechanism works, the output voltage from the DC/DC card and the AC Adapter continues to be blocked. To cancel the mechanism, disconnect the battery pack and the AC Adapter and then reconnect them.

Standby Battery Test

1. Remove the standby battery. (See "1040 Backup, Standby Battery" on page 55.)
2. Measure the battery voltage between the connector pins as shown below.




Wire	Voltage (V dc)
Red (+)	+2.7 to +4.5
Black (-)	Ground

If the voltage is not correct, replace the standby battery.

Also check the voltage across the pins of the J12 connector for the standby battery with the AC Adapter connected to the system and with the system power switch off. If the voltage is less than 3.9V, replace the DC/DC card first. If the voltage is more than 3.9V, the original DC/DC card was bad. If the voltage is still low, replace the system board. If the battery voltage is correct and the system is still in suspend mode, a short circuit or a failure in the system board is likely. Replace the system board.

Backup Battery Test

1. Remove the backup battery. (See "1040 Backup, Standby Battery" on page 55.)
2. Measure the battery voltage between the connector pins as shown below.



Wire	Voltage (V dc)
Red (+)	+2.7 to +3.7
Black (-)	Ground

If the voltage is not correct, replace the backup battery.

If the voltage is correct, a short circuit or a failure in the system board has occurred. Replace the system board.

Travel Quick Charger Test

Do the following if you suspect a Travel Quick Charger problem.

1. Make sure that the battery storage switch is in the ON (I) position. Verify that the battery voltage and the resistance are within the range described in "Battery Pack Test" on page 15.
2. Connect the power cord to the AC Adapter. Connect the AC Adapter output plug to the Travel Quick Charger. The power indicator should turn on. If the indicator does not turn on, recheck the connections of the power cord.
3. Install the battery pack. The charging indicator should turn on yellow after about 5 seconds.
4. Within 2 hours, the battery pack should be fully charged and the charging indicator should change from yellow to green.

If the charger does not work as just stated, replace the Travel Quick Charger.


For other functions and operations, refer to the Travel Quick Charger manual.

Maintenance Utility

The Maintenance Utility is part of Easy-Setup. It consists of two items:

- System Info
- SCSI Format

To start the Maintenance Utility, press the **Ctrl + V** keys in the **Super Test** screen. The following screen appears:




System Information

Select **System Info** in the Maintenance Utility menu. This screen shows the Firmware Part Number, Installed Memory, and Serial Number of the system board.

Whenever you replace the system board, specify the serial number of the new system board on this screen.

If the layout of your keyboard for alphanumeric keys is different from the layout on the following page, use the layout on the following page when you type the new system information.



SCSI Format

Do the following to format the disk:

Warning: Make sure the drive address for the disk to be formatted is correct. This procedure erases all information on the disk.

1. Select **SCSI Format** on the Maintenance Utility menu.
2. Select the drive from the menu.
3. Follow the instructions on the screen.

Numeric Error Codes

If an error is detected by the diagnostic test or POST, an eight-digit error code is displayed. The error code indicates the suspected FRUs. The most likely cause is listed first.

In the following error codes, **X** can be any number.

Note

For IBM devices not supported by the ThinkPad Power Series 820 diagnostic codes, refer to the manual for that device.

Symptom or Error	FRU and Action
00010000 (Processor)	CPU card System board
0001500X (Flash)	System board
0001550X (Interrupt)	CPU card System board
0001600X (CMOS/NVRAM)	Backup battery System board
000170XX (NVRAM/EEPROM)	Backup battery System board
00020000 (Memory error)	System board
000210Y0 (Memory error)	Memory card in slot Y Y Memory Card 1 DIMM card in slot 1 2 DIMM card in slot 2 3 DIMM card in slot 3 System board
000300XX (Keyboard)	Keyboard System board
00063XX0 (Diskette drive)	Diskette drive Media System board
000640D0 (Diskette drive)	No media found Media is defective Diskette drive System board

Symptom or Error	FRU and Action
0006XXX0 (Diskette drive)	Diskette drive System board
00110001 (Serial port)	Disconnect any I/O device from the serial port. System board
001100XX (Serial port)	System board
00140006 (Parallel port)	Disconnect any I/O device from the parallel port. System board
0014000X (Parallel port)	System board
00140010 (Enhanced parallel port)	Check the parallel port and disconnect any I/O from the parallel port. System board
00140011 (Enhanced parallel port)	System board
0024000X (Video)	Entry video card or motion video card System board
0037XXX0 (SCSI controller)	System board
00370730 (SCSI controller)	Device ID conflict
00800004 (PCMCIA)	PCMCIA wrap plug not installed. System board
008000XX (PCMCIA)	System board
008600X0 (Mouse)	Keyboard assembly System board Mouse
01291000 (L2 cache)	CPU card System board
02XXXXX0 (SCSI)	SCSI drives System board
0250100X (Audio)	Audio card Sub audio card System board
10EDXXXX (Video)	Motion video card System board

Symptom-to-FRU Index

The symptom-to-FRU index lists the symptoms and errors and the possible causes. The most probable cause is listed first. Use this index to help you decide which FRUs to have available when servicing a computer.

No-Beep Symptoms

Symptom or Error	FRU and Action
No beep, power-on LED not lit, and a blank LCD during POST. (See "Power Systems Checkout" on page 12 before replacing any FRUs.)	DC/DC card AC adapter Battery CPU card Memory card System board
No beep, power-on LED lit, and a blank LCD during POST. (See "Power Systems Checkout" on page 12 before replacing any FRUs.)	DC/DC card CPU card Memory card System board
No beep during POST but system runs OK.	System board (speaker) Keyboard
No beep and a blank, unreadable, or flashing LCD.	LCD assembly Interposer card DC/DC card Base memory card System board
No beep and the battery power status LED keeps blinking yellow, orange, and green repeatedly while charging the battery with the AC Adapter.	Battery pack DC/DC card System board
No beep and the battery power status LED turns orange while charging the battery with the AC adapter.	Battery pack

Miscellaneous Symptoms


Symptom or Error	FRU and Action
LCD screen unreadable or characters missing pels.	LCD assembly Interposer card Video card System board
One or more keys do not work.	Keyboard System board
LCD backlight not functioning.	LCD assembly Interposer Card System board
LCD backlight intensity not adjustable.	LCD assembly Interposer card System board
LCD contrast not adjustable.	LCD assembly Interposer card System board
System hangs or intermittently hangs. (See "Undetermined Problems" on page 10 before replacing any FRUs.)	Press the power shutdown switch If "ThinkPad Power Series" is displayed continuously, replace the system board. If the user's defined screen does not appear, ensure there is no problem with the operating system; then replace the system board.
The system does not suspend or resume.	Operating system System board
The system does not power off.	Press power shutdown switch System board
Real-time clock is inaccurate.	Backup battery System board
Printer problems. (See "Printer" on page 11 .)	System board Parallel port device cable
Serial or parallel port device problems.	Device Device cable System board

Symptom or Error	FRU and Action
The battery power status LED keeps blinking yellow while charging the battery with the AC adapter.	Battery pack
Incorrect LED status, but system runs OK.	System board

If the problem remains, see “Undetermined Problems” on page 10.

(This page is left blank intentionally.)

Parts Listing



FRU List

1	30H1418	. Display Bezel Assembly(VGA)
1	30H1425	. Display Bezel Assembly(SVGA)
2	84G4529	. Display Assembly, TFT(VGA)
2	85G2050	. Display Assembly, TFT(SVGA)
3	30H1419	. Cover - Display Rear Assembly
4	30H1420	. Hinge - Display
5	30H1421	. Cable Assembly(VGA)
5	30H1427	. Cable Assembly(SVGA)
6	30H1422	. Cable - LCD Power
7	30H1423	. Center Cover Assembly
8	-	. Mic Assembly
9	(Note)	. Keyboard Assembly
9a	-	. Security Bracket
10	30H1445	. Speaker - Left
11	30H1444	. Speaker - Right
12	85G0156	. Battery - W/T
13	85G0166	. FDD Bezel
14	85G0165	. FDD Assembly (FDD External Kit)
15	30H1471	. Hard Disk Drive Assembly 1.2GB
15	85G0157	. Hard Disk Drive Assembly 810MB
15	85G0153	. Hard Disk Drive Assembly 540MB
16	85G0154	. CD-ROM Drive Assembly
17	85G0131	. Shield Assembly
18	85G0151	. Card - Audio
19	85G0130	. Card - Interposer
20	85G0129	. Card - DC/DC
21	85G0139	. Battery Top Cover
22	85G0142	. Backup Battery
23	85G0086	. Sub Battery
24	85G0141	. Front Stay-Left
25	85G0140	. Front Stay-Right
26	84G6545	. DIMM - 8MB
26	84G4324	. DIMM - 16MB
27	85G0152	. Card - for DIMM
28	30H1424	. Cover-Video Connector
29	85G0128	. Rear Cover - D-Sub
30	85G0148	. Card - Main Planar
31	85G0149	. Card - Video
31	30H1451	. Card - Motion Video
32	30H1417	. Sheet-Audio Bottom
33	85G0135	. Door - I/O (D-Sub)
34	85G0136	. Door - ISA Bus
35	85G0126	. Base Cover Assembly
36	85G0150	. CPU Card Assembly
37	85G0134	. Cover for CPU Cover
38	85G0127	. Door Assembly - PCMCIA
39	85G0167	. AC Adapter - W/T
39	85G0168	. AC Adapter - Japan
-	85G0132	. Thermal Pad-CPU
-	85G0169	. Travel Quick Charger-W/T
-	85G0170	. Travel Quick Charger-Japan

-	30H1415	. Shade
-	30H1450	. Video Connector Cable
-	85G0137	. Mecha GBM - Parts Group 1
40	-	.. Insulator - Audio Upper
41	-	.. Insulator - DIMM Upper
-	-	.. Holder - DIMM Insulator
-	-	.. Mic Holder
-	-	.. Screw Cover D7.5
-	-	.. Screw - M2.5X3.5(T=0.8)
-	-	.. Screw - M2.5X6 (Bind)
-	-	.. Screw - M2.5X8 (Bind)
-	-	.. Screw - M2.5X18 (Bind)
-	-	.. Stud - Expansion Stay
-	-	.. Hex Stud - D/Sub
-	-	.. Spring Shade
-	-	.. EMI Spring-FDD
-	-	.. Motion Video Hole Cover
-	-	.. Stopper-Spring
-	-	.. Security Plate
-	85G0138	. Mecha GBM - Parts Group 2
42	-	.. Bracket - Hinge Right
43	-	.. Bracket - Hinge Left
-	-	.. Stay-Expansion
-	-	.. Bracket - DC-DC Card
-	-	.. Spacer - DC-DC Conn MT
-	85G0143	. Mecha GBM - Parts Group 3
44	-	.. Cap Hinge - Left
45	-	.. Cap Hinge - Right

Keyboard Assembly

85G0171	U.S. English
85G0172	U.K. English
85G0173	German
85G0174	Swiss German
85G0175	French
85G0176	Swiss French
85G0177	Italian
85G0178	Swedish
85G0179	Dutch
85G0180	Spanish
85G0181	Danish
85G0182	Belgian
85G0183	Norwegian
85G0184	Arabic
85G0185	Hebrew
85G0186	Portuguese
85G0187	Turkish
85G0188	Greek
85G0189	Latin American
85G0190	Canadian French
85G0192	Japanese

Option List

30H1369	Battery Pack, U.S.
30H1371	Battery Pack, EMEA
30H1372	Battery Pack, Japan
92G7255	8MB DIMM Card
84G6541	8MB DIMM Card, Japan
92G7257	16MB DIMM Card
84G4351	16MB DIMM Card, Japan
30H1388	Hard Disk Drive 540MB, U.S.
30H1390	Hard Disk Drive 540MB, EMEA
30H1391	Hard Disk Drive 540MB, Japan
30H1392	Hard Disk Drive 810MB, U.S.
30H1394	Hard Disk Drive 810MB, EMEA
30H1395	Hard Disk Drive 810MB, Japan
30H1467	Hard Disk Drive 1.2GB, U.S.
30H1468	Hard Disk Drive 1.2GB, EMEA
30H1469	Hard Disk Drive 1.2GB, Japan
06G5985	Microphone - Peavy
30H1519	Mouse - 3 Button, U.S.
30H1520	Mouse - 3 Button, EMEA
30H1521	Mouse - 3 Button, Japan
(Note 1)	Travel Quick Charger
(Note 2)	AC Adapter

Note 1: Travel Quick Charger

30H1373	U.S.
30H1375	U.K.
30H1378	EMEA
30H1379	Switzerland
30H1380	Italy
30H1381	Denmark
30H1382	Israel
30H1383	Latin American
30H1384	Japan

Note 2: AC Adapter


30H1403	U.S.
30H1405	U.K.
30H1406	EMEA
30H1407	Switzerland
30H1408	Italy
30H1409	Denmark
30H1410	Israel
30H1411	Latin American
30H1412	Japan

Accessories

The warranty times for accessories are different from the warranty time for the system unit. Some of the accessories related to services are:

49G2169	Key Guard, U.S.
54G0443	Key Guard, EMEA
54G0441	Keyboard/Mouse Connector

Power Cords



Index Power Cords

Warning: Use the power cord certified for your country.

1	Colombia, U.S., Venezuela	13F9959
2	U.K.	14F0032
2	Hong Kong, Singapore, U.K.	14F0033
3	EMEA	13F9978
4	Italy	14F0068
5	Australia, New Zealand	13F9940
6	Denmark	13F9996
7	Israel	14F0086
8	Bangladesh, Pakistan, Sri Lanka, South Africa	14F0015
9	Switzerland	14F0050
10	Thailand	1838574
11	Japan, 2-pin	6454377

ThinkPad Power Series 820 Hardware Maintenance Reference

This section provides the reference information for the computer. It includes:

- Product overview
- Component descriptions
- Operating requirements
- Specifications
- Special tools
- Repair information
- Removals and replacements
- Locations

Product Overview

The computer, the ThinkPad Power Series 820, is a lightweight, portable computer with a CD-ROM drive. The keyboard is the primary means of data entry and editing; however, a mouse can be attached to the computer via a keyboard cable with a separator.

The portability of the computer allows you to operate the computer in various places. It is ideally suited to the mobile professional who requires a portable computer for work. The computer is powered by a rechargeable, nickel-metal hydride (Ni-MH) battery pack.

The video capturing function is available on selected models.

Product Description

The computer has the following standard features:

- 100-MHz microprocessor
- Color liquid crystal display (LCD)
- Minimum of 16MB DIMM , expandable up to 48MB
- Video controller
- External diskette drive(1.44MB)
- 2.5-inch, 1.2GB, 810MB, or 540MB hard disk drive
- CD-ROM drive
- Removable 3.5-inch diskette drive
- Audio card
- Power cord
- Intelligent battery pack (rechargeable)
- Backup battery

The computer has the following external indicators, controls, connectors, and ports:

- AC Adapter connector
- DIMM card slots
- PCMCIA sockets
- IBM PS/2 Mouse/Keyboard connector
- SCSI connector
- Expansion connector
- External diskette drive connector
- External display connector
- Parallel port connector
- Serial port connector
- Headphone jack
- Microphone jack
- Audio volume control
- Contrast control slide switch
- Brightness control slide switch
- CD-ROM eject button
- CD-ROM in-use light
- CD-ROM emergency eject button
- Power shutdown switch
- Power switch
- Battery power status light
- PC card in-use light
- Diskette drive in-use light
- Hard disk drive in-use light
- Numeric lock light
- Caps lock light
- Scroll lock light
- Suspend mode light

- Power-on light

Options

Several options are available for the computer. See“Option List” on page 33 .

Option Compatibility

The computer has no internal expansion slots for standard PC or PS/2 adapters.

Accessories

Several accessories are available for the computer. See“Accessories” on page 34 .

Component Descriptions

System Board

The system board contains the computer logic, memory, and adapters.

Microprocessor

The PowerPC microprocessor interprets and performs the instructions. Its 32-bit processor runs at 100MHz and contains an internal cache which has a 16KB instruction cache and a 16KB data cache. Its operating voltage is +3.3 V dc.

Flash ROM

The 512KB flash ROM contains the POST, BOOT, Resident Setup and Resident Diagnostic code. Algorithms for writing data into the flash ROM after the computer is manufactured are provided. After power-on, the initial code for the ROM is supplied from the device. A maximum ROM space of 16MB is reserved; however, the system board uses 512KB.

RT/CMOS/NVRAM

These provide the real-time clock and calendar function and store configuration and vital product data.

The stored data in the RT/CMOS/NVRAM are kept active by the backup battery when the system power is not on. If the stored data is lost because of a depleted or removed backup battery, use **Easy Setup** to restore the data.

EEPROM

A 64-by-16 type-A EEPROM contains the security passwords.

Power Management System

The power management system controls the power applied to the computer. This reduces the power drain on the battery when the computer power is on, but not actively being used.

LCD

The VGA LCD supports a maximum of 640 by 480 pels.

The SVGA LCD supports a maximum of 800 by 600 pels. The LCD control logic provides the LCD support functions, which include bias voltage, backlight (brightness) control, and contrast control. Prior to replacement of the LCD, refer to the notice on page 58.

Diskette-Drive Controller

The controller connects to the diskette drive through one, 26-pin cable connector on the system board. Signals and voltages are supplied through the connector to the drive. These signals and voltages can operate the computer's 3.5-inch external diskette drive.

For the standard model, a CD-ROM drive is built in. For users that want to use diskettes, the system unit has a connector for the detachable external diskette drive.

For users that want to replace the CD-ROM drive with a diskette drive, a kit is provided. Both the internal and external diskette drives can be connected at the same time.

Serial Port

The serial port is fully programmable and supports asynchronous communication. The 9-pin, D-shell connector provides the signals to drive a standard EIA-232D device.

Parallel Port

The parallel port allows the attachment of devices that accept eight bits of parallel data at standard transistor-transistor logic (TTL) levels. The port can be used as a general input and output port for any device or application that matches its input and output capabilities. It has a 25-pin, D-shell connector and is designed primarily for printers.

External Input-Device Connector

The external input-device connector is located at the right-rear of the computer and accepts an external keyboard, mouse, or numeric keypad.

The keyboard/mouse connector (a Y-shaped connector with cable and available as an option) must be used when the external keyboard is attached. You can directly attach an external numeric keypad and a 2-button/3-button mouse to the external input-device connector.

External Display Connector

The display connector is used to connect an external monitor.

Operating Requirements

The following describes the operations that occur after power is applied and until the minimum operating requirements are met:

Power-On Self-Test (POST)

The POST is initiated automatically each time the system power is switched on. The POST is a series of system checks and initialization. The POST checks only those areas that permit the system to be operational enough to boot the operating system.

After a successful POST, control is then given to the operating system.

Memory Requirements and Limitations

The computer has three DIMM card sockets on the memory board.

One or two sockets are occupied by 16MB DIMM cards as standard configurations. An additional 8MB or 16MB DIMM card can be installed into the other socket for a total of up to 48MB of system memory.

Specifications

System

Size

- Width: 298 mm (11.7 in.)
- Depth: 211 mm (8.3 in.)
- Height: 55 mm (2.1 in.)

Weight

- System unit (CD-ROM model): 3.4 kg (7.5 lb)
- Battery pack: 0.7 kg (1.5 lb)

Environment

- Air temperature:
 - System on: 5°C to 35°C (41°F to 95°F)¹
 - System on (with diskette): 10°C to 35°C (50°F to 95°F)
 - System off: 5°C to 43°C (41°F to 109°F)
- Humidity:
 - System on: 8% to 80%
 - System off: 8% to 80%
- Maximum altitude: 2438 m (8000 ft)²

Heat Output

160 British Thermal Units (BTUs) per hour (47 watts per hour) with power supplied from the AC Adapter.

¹ A maximum of 32°C (90°F) at altitudes higher than 915 m (3000 ft).

² A maximum temperature of 31.3°C (88°F) with no pressurized condition.

AC Adapter

Input Voltage

- Low range
 - Minimum: 90 V ac
 - Maximum: 137 V ac
- High range
 - Minimum: 180 V ac
 - Maximum: 265 V ac
- Frequency range
 - Minimum: 47 Hz
 - Maximum: 63 Hz

Output Voltage

- Operating mode: +20 V dc
- Charging mode
 - Minimum: +5.6 V dc
 - Maximum: +12.6 V dc

Maximum Current

5.0 A

Travel Quick Charger

Input Voltage

- Minimum: 17.8 V ac
- Maximum: 21.0 V ac

Output Voltage

- Nominal 20 V dc

Maximum Current

5.0 A

Special Tools

The following tools are used to service the computer.

- Super Test (Advanced Diagnostics) in Easy Setup
- PCMCIA Wrap Card (P/N 35G4680)
- Tri-Connector Wrap Plug (P/N 72X8546)
- Scratch Diskette

Note: These tools are used in Step 014 on page 8.

- Maintenance Utility in Easy Setup
 - System Information
 - SCSI Format

Note: Refer to "Maintenance Utility" on page 21.

- Box Wrench (5m/m, 7m/m)

Repair Information

This section contains information about removals and replacements, and locations.

- Do not damage any part. Only certified and trained personnel should service the computer.
- The arrows in the "Removals and Replacements" section show the direction of movement to remove a field-replaceable unit (FRU) or to turn a screw to release the FRU. The arrows are marked in numeric order to show the correct sequence of removal.
- When other FRUs must be removed before removing the failing FRU, they are listed at the top of the page. Go to the removal procedure for each FRU listed, remove the FRU, and then continue with the removal of the failing FRU.
- To replace a FRU, reverse the removal procedure and follow any notes that pertain to replacement. See "Locations" for internal cable connections and arrangement information.
- When replacing a FRU, use the correct screw size as shown in the procedures.

CAUTION


Before removing any field-replaceable unit (FRU), switch off the power of the computer, unplug all power cords from electrical outlets, disconnect any interconnecting cables, then remove the battery pack. The batteries used (battery pack, standby battery, and backup battery) contain small amounts of harmful substances. Do not disassemble it, throw it into fire or water, or short-circuit it. Dispose of the battery pack as required by local ordinances or regulations.

WARNING

The system board and memory card are sensitive to, and can be damaged by, electrostatic discharge. Establish personal grounding by touching a ground point with one hand before touching these units. An electrostatic discharge (ESD) strap must be used to establish personal grounding.

Removals and Replacements

1000 Opening the Display Assembly





Note: Open the display assembly as shown below to prevent the computer from falling backward when some devices are removed.




1005 Opening the Keyboard Assembly

- Opening the Display Assembly (1000)




1010 Speaker Assembly

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)



1015 Battery Pack

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)




CAUTION

Battery packs are capable of delivering high currents for a significant amount of time. Do not short-circuit the battery terminals.


1020 HDD Assembly

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)




1025 FDD Assembly

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)



1030 CD-ROM Drive Assembly

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)




1035 DIMM (Memory) Card

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)
- Battery Pack (1015)
- HDD Assembly (1020)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)


Memory Card

When you install a memory card, make sure the card is installed with the corner notch toward the left side; then check that both sides of the card are firmly latched.



1040 Backup, Standby Battery

- Opening the Display Assembly (1000)
- Opening the Keyboard Assembly (1005)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)



CAUTION

The backup battery is a lithium battery and can cause a fire, explosion, or severe burn if not properly used or disposed of. Do not recharge it, disassemble it, heat it above 100°C (212°F), incinerate it, or expose its cell contents to water. Dispose of the battery as required by local ordinances or regulations. When replacing the battery, use the one that is available as a FRU. Use of a wrong battery could result in ignition or explosion of the battery. Replacement batteries can be ordered from IBM or IBM Authorized Dealers.


NOTE

Real-time clock, configuration, and power-on password data will be lost when the backup battery is removed. Always reset this data after the battery has been replaced.

1045 Center Cover Assembly, Mic Assembly


- Opening the Display Assembly (1000)

Center Cover Assembly 1 - 3
Mic Assembly 1 - 4



1050 Keyboard Assembly

- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)



1055 Display Assembly

LCD FRU Replacement Notice

CAUTION

The liquid crystal display (LCD) includes a fluorescent light that contains a small amount of mercury. Dispose of the LCD assembly as required by local ordinances or regulations.

The LCD is made of glass, and rough handling or dropping the computer can cause the LCD to break. If the LCD breaks and the internal fluid gets into your eyes or on your hands, immediately wash the affected areas with water for at least 15 minutes; then get medical care if any symptoms are present after washing.

If missing or discolored dots appear on the LCD, carefully read the following note to determine whether you should replace the LCD.

Important

A small number of missing, discolored, or lighted dots (on all the time) is characteristic of LCD technology, but excessive pixel problems can cause viewing concerns. The LCD should be replaced if the number of dots satisfies the following condition:

- The number of missing, discolored, or colored dots in any colored background is 21 or more.


Note: When you need to clear the LCD, gently wipe the LCD with a dry, soft cloth. Do not use alcohol or detergent to clean the LCD.

To avoid damaging the LCD, do not scratch or apply any force to its surface.

- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)
- Keyboard Assembly (1050)

Hinge Cap 1

Display Assembly 1 - 5



Display bezel Assembly 1 - 2


Display Assembly 1 - 3

LCD Interface Cable Assembly 1 - 4

LCD Power Cable Assembly 1 - 5


LCD Hinge Assembly 1 - 6

Display Rear Cover Assembly 1 - 7



1060 Shield Assembly


- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)
- Keyboard Assembly (1050)
- Battery Pack (1015)
- HDD Assembly (1020)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)
- Display Assembly (1055)




1065 Interposer Card, DC/DC Card

- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)
- Keyboard Assembly (1050)
- Battery Pack (1015)
- HDD Assembly (1020)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)
- Display Assembly (1055)
- Shield Assembly (1060)

Interposer Card 1 - 2
DC/DC Card 1 - 3




1070 CPU Card




1075 Video Card, System Board

- CPU Card (1065)
- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)
- Keyboard Assembly (1050)
- Battery Pack (1015)
- HDD Assembly (1020)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)
- Backup, Standby Assembly (1040)
- Display Assembly (1055)
- Shield Assembly (1060)
- Interposer Card, DC/DC Card (1065)



Note: Do not lose the metal ring stud **A**.

Video Card 1-6 System Board 1-7




Note: **3** Motion video card model only.

Serial Number

When you replace the system board, do not forget to change the serial number of the system board. Refer to "System Information" on page 22.


1080 Audio Card

- CPU Card (1065)
- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)
- Keyboard Assembly (1050)
- Battery Pack (1015)
- HDD Assembly (1020)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)
- Display Assembly (1055)
- Shield Assembly (1060)
- Interposer Card, DC/DC Card (1065)
- Video Card, System Board (1075)



1085 Memory Board

- CPU Card (1065)
- Opening the Display Assembly (1000)
- Center Cover Assembly (1045)
- Keyboard Assembly (1050)
- Battery Pack (1015)
- HDD Assembly (1020)
- FDD Assembly (1025)
- CD-ROM Drive Assembly (1030)
- Display Assembly (1055)
- Shield Assembly (1060)
- Video Card, System Board (1075)
- Interposer Card, DC/DC Card (1065)
- Audio Card (1080)





Locations

Front View


- 1 LCD Latches
- 2 LCD Screen
- 3 Contrast Control Slide Switch
- 4 Brightness Control Slide Switch
- 5 Indicator Panel
- 6 Microphone
- 7 External Input-Device Connector
- 8 PCMCIA Slots
- 9 Audio PC Card Jack
- 10 Power Switch
- 11 Speakers
- 12 Keyboard Latches
- 13 Volume Control
- 14 Microphone Jack
- 15 Headphone Jack
- 16 CD-ROM Eject Button
- 17 Removable Diskette Drive
- 18 Click Buttons
- 19 TrackPoint III
- 20 Keyboard
- 21 Indicators

- 1 Battery Power Status Light
- 2 PC Card In-Use Light
- 3 Diskette Drive In-Use Light
- 4 Hard Disk Drive In-Use Light
- 5 Numeric Lock Light
- 6 Caps Lock Light
- 7 Scroll Lock Light
- 8 Suspend Mode Light
- 9 Power-On Light




Bottom and Rear Side View

- 1** Locking Lever
- 2** CPU Card
- 3** System Bus Connector
- 4** Power Jack
- 5** Integrated Video Jack
- 6** External-Display Connector
- 7** Serial Connector
- 8** Parallel Connector
- 9** External Diskette Drive Connector
- 10** SCSI-2 Connector
- 11** Power Shutdown Switch
- 12** Rear Door




Inside View

- 1** Speaker Assembly
- 2** Security Bracket
- 3** Center Cover Assembly
- 4** Interposer Card
- 5** System Board
- 6** Audio Card
- 7** Removable Hard Disk Drive
- 8** Standby Battery
- 9** Backup Battery
- 10** CD-ROM Drive
- 11** Memory Card
- 12** Rechargeable Battery Pack
- 13** Video Card
- 14** DC/DC Card
- 15** Keyboard Assembly



System Board Connectors



Connector	Device
S1	Power Shutdown Switch
J1	System Bus Connector
J2	External Display Connector
J3	Serial Connector
J4	Parallel Connector
J5	External Diskette Drive Connector
J6	SCSI-2 Connector
J7	External Input-Device Connector
J8	Interposer Card
J10	DC/DC Card
J11	Diskette/CD-ROM Drive Connector
J12	Standby Battery Connector
J13	Backup Battery Connector
J14	Video Card
J15	CPU card
J16	Memory Card
J17	Password Override Pin
J18	Audio Card



© Copyright
International Business
Machines Corporation 1995.
All Rights Reserved.

References in this
publication to IBM
products or services do not
imply that IBM intends
to make them available
outside the United States.

30H2388

Printed in U.S.A.

30H2388



S30H-2388-00



002-10474